

Transformer - 300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V

Item PX300



PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

FEATURES

- ► Mounting brackets on the top and bottom
- ► Built-in circuit protection disconnects power temporarily in case of overload
- ► Complies with NEC Code 680.23 requirements for underwater luminaries
- ► Noise filter accessory available separately (part number ET-NF).

APPLICATIONS

- ► Landscape Lighting
- ► Underwater Lighting

TECHNICAL DATA

General	
Model Number	PX300
Description	300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V
UPC Code	078275024106
Brand	Intermatic
Country of Origin (Intermatic)	MALAYSIA
Warranty Period	1-Year limited

Mechanical Specifications

Enclosure Type 3R Beige metal

Dimensions		
Product Dimensions (H x W x D) in	7.25 x 5.25 x 4.5 in	
Knockout Dimensions Bottom	(4) combination 1/2" - 3/4"	
Knockout Dimensions Back	(2) combination 1/2" - 3/4"	
Knockout Dimensions Left	(2) combination 1/2" - 3/4"	
Knockout Dimensions Right	(2) combination 1/2" - 3/4"	

Material Specifications

Color Ivory

Electrical Specifications	
Output Voltages	12 VAC; 13 VAC; 14 VAC
Maximum Power Consumption (W)	300 W
Transformer (W)	300
Transformer Input Voltage	3 A, 120 VAC, 60 Hz
Transformer Output Voltage	12, 13, 14 VAC

Packaging



Shipping Weight (lbs)	11.251
Product Weight (kg)	4.99
Unit Carton Dimensions (H x W x L) in	7.88 x 4.56 x 5.69 in
Product Weight (lbs)	11

Standards and Certifications	
CSA Certification	cCSAus
Other Certifications and Compatibilities	NEC Code 680.23
California Proposition 65	DEHP
RoHS Certification	N/A



ACCESSORIES



ET-NF

RC Snubber Noise Filter 24-277 VAC for Electronic Controls