

## Transformer - 100 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V

Item PX100



### PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12,13 and 14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

### FEATURES

- Mounting brackets on the top and bottom
- Built-in circuit protection disconnects power temporarily in case of overload
- Complies with NEC Code 680.23 requirements for underwater luminaries
- Noise filter accessory available separately (part number ET-NF).

### APPLICATIONS

- Landscape Lighting
- Underwater Lighting

### TECHNICAL DATA

#### General

Model Number	PX100
Description	100 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V
UPC Code	078275024090
Brand	Intermatic
Country of Origin (Intermatic)	U.S.A.
Warranty Period	1-Year limited

#### Mechanical Specifications

Enclosure Type	3R Beige metal
----------------	----------------

#### Dimensions

Product Dimensions (H x W x D) in	7.25 x 5.25 x 4.5 in
Knockout Dimensions Bottom	(4) combination 1/2" - 3/4"
Knockout Dimensions Back	(2) combination 1/2" - 3/4"
Knockout Dimensions Left	(2) combination 1/2" - 3/4"
Knockout Dimensions Right	(2) combination 1/2" - 3/4"

#### Material Specifications

Color	Beige
-------	-------

#### Electrical Specifications

Output Voltages	12 VAC; 13 VAC; 14 VAC
Maximum Power Consumption (W)	100 W
Transformer (W)	100
Transformer Input Voltage	1 A, 120 VAC, 60 Hz
Transformer Output Voltage	12, 13, 14 VAC

#### Packaging

Shipping Weight (lbs)	6.486
Unit Carton Dimensions (H x W x L) in	7.88 x 4.56 x 5.69 in

Standards and Certifications	
UL Certification	UL Swimming Pool Transformer, UL1838, and UL379
Other Certifications and Compatibilities	NEC Code 680.23
California Proposition 65	DEHP
RoHS Certification	N/A

---

## ACCESSORIES



ET-NF

RC Snubber Noise Filter 24-277 VAC for Electronic Controls