

Transformer - 600 W Pool & Spa Safety Transformer, Stainless Steel Enclosure, Input 120V, Output 12,13,14V

Item PX600S



PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

FEATURES

- Mounting brackets on the top and bottom
- Built-in circuit protection disconnects power temporarily in case of overload
- Complies with NEC Code 680.23 requirements for underwater luminaries
- Noise filter accessory available separately (part number ET-NF).

APPLICATIONS

- Landscape Lighting
- Underwater Lighting

TECHNICAL DATA

General

Model Number	PX600S
Description	600 W Pool & Spa Safety Transformer, Stainless Steel Enclosure, Input 120V, Output 12,13,14V
UPC Code	078275079861
Brand	Intermatic
Country of Origin (Intermatic)	MEXICO
Warranty Period	1-Year limited

Mechanical Specifications

Enclosure Type	3R Brown stainless steel
----------------	--------------------------

Dimensions

Product Dimensions (H x W x D) in	10 x 10 x 5.375 in
Knockout Dimensions Bottom	(2) combination 1/2" - 3/4", (4) combination 3/4" - 1"
Knockout Dimensions Back	(2) combination 1/2" - 3/4"
Knockout Dimensions Left	(2) combination 1/2" - 3/4"
Knockout Dimensions Right	(2) combination 1/2" - 3/4"

Electrical Specifications

Output Voltages	12 VAC; 13 VAC; 14 VAC
Maximum Power Consumption (W)	600 W
Transformer (V)	600
Transformer Input Voltage	6 A, 120 VAC, 60 Hz
Transformer Output Voltage	12, 13, 14 VAC

Packaging

Shipping Weight (lbs)	31.983
Unit Carton Dimensions (H x W x L) in	11.751 x 6.001 x 10.751 in

Standards and Certifications

UL Certification	UL Swimming Pool Transformer
Other Certifications and Compatibilities	NEC Code 680.23
California Proposition 65	DEHP
RoHS Certification	N/A

ACCESSORIES



ET-NF

RC Snubber Noise Filter 24-277 VAC for Electronic Controls