

## Radio Receiver - Radio Receiver with manual ON/OFF button

Item RC613L



### PRODUCT DESCRIPTION

Control loads with the receiver mounted ON/OFF button or wirelessly via a remote transmitter. For indoor/outdoor use. Turn your pool lights on from any spot around your house.

### FEATURES

- ▶ Respond to handheld transmitter (provided separately below)
- ▶ For indoor/outdoor use
- ▶ Handle a variety of switching applications
- ▶ Enable connected loads to be turned ON/OFF remotely
- ▶ Maximum range 100 ft
- ▶ Beige outdoor grade plastic enclosure

### APPLICATIONS

- ▶ Motor Control
- ▶ Pump Control

### TECHNICAL DATA

General	
Model Number	RC613L
Description	Radio Receiver with manual ON/OFF button
UPC Code	078275071803
Brand	Intermatic
Country of Origin (Intermatic)	MEXICO
Warranty Period	1-Year limited

Control Specifications	
Number of Radio Channels	1
Reception Range (ft)	100
Reception Range (m)	30.48

Dimensions	
Product Dimensions (H x W x D) in	4.5 x 3 x 1.75 in
Wire Lead Length (in)	36

Material Specifications	
Color	Beige
Body Material	Plastic

Load Ratings	
Motor Load Ratings NO Ranges	1 HP @ 120 VAC
Tungsten Incandescent Load Ratings NO Ranges	10 A, 1200 W

Electrical Specifications	
Switch Type	SPST

Packaging	
-----------	--

Shipping Weight (lbs)	0.649
Unit Carton Dimensions (H x W x L) in	3.5 x 3.75 x 5.75 in

#### Environmental Specifications

Usage Environments	Indoor; Outdoor
--------------------	-----------------

#### Standards and Certifications

CSA Certification	cCSAus
California Proposition 65	DEHP
RoHS Certification	N/A

---

## ACCESSORIES



RC939  
Handheld 3-Channel Radio Transmitter