

Transformer - 300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V

Item PX300



PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

FEATURES

- ▶ Mounting brackets on the top and bottom.
- ▶ Built-in circuit protection disconnects power temporarily in case of overload.
- ▶ Complies with NEC Code 680.23 requirements for underwater luminaries.
- ▶ Noise filter accessory available separately (part number ET-NF).

APPLICATIONS

- ▶ Landscape Lighting
- ▶ Underwater Lighting

TECHNICAL DATA

General

Model Number	PX300
Description	300 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V
UPC Code	078275024106
Brand	Intermatic
Country of Origin (Intermatic)	MALAYSIA
Warranty Period	1-Year limited

Mechanical Specifications

Enclosure Type	3R Beige metal
----------------	----------------

Dimensions

Product Dimensions (H x W x D) in	7.25 x 5.25 x 4.5 in
Knockout Dimensions Bottom	(4) combination 1/2" - 3/4"
Knockout Dimensions Back	(2) combination 1/2" - 3/4"
Knockout Dimensions Left	(2) combination 1/2" - 3/4"
Knockout Dimensions Right	(2) combination 1/2" - 3/4"

Material Specifications

Color	Ivory
-------	-------

Electrical Specifications

Output Voltages	12 VAC; 13 VAC; 14 VAC
Maximum Power Consumption (W)	300 W
Transformer (W)	300
Transformer Input Voltage	3 A, 120 VAC, 60 Hz
Transformer Output Voltage	12, 13, 14 VAC

Packaging

Shipping Weight (lbs)	11.251
Unit Carton Dimensions (H x W x L) in	7.88 x 4.56 x 5.69 in
Product Weight (lbs)	11
Product Weight (kg)	4.99

Standards and Certifications

UL Certification	UL Swimming Pool Transformer
Other Certifications and Compatibilities	NEC Code 680.23
California Proposition 65	DEHP
RoHS Certification	N/A

ACCESSORIES



ET-NF
RC Snubber Noise Filter 24-277 VAC for Electronic Controls